

Wine Country Productions, Inc.
SEQUENTIAL Product Specialists
Sales • Service • Spare Parts

1572 Park Crest Court #505
San Jose, California 95118

SEQUENTIAL
Publications Department

CN2000-5A
April, 1987

PROPHET 2000 / 2002
VERSION 4.0, 4.1, 4.2, & 4.3B
MODEL 879 1-MEGAWORD RAM UPDATE

GENERAL INFORMATION

This update (software level 4.1) adds an additional 512K words of sound RAM to the Prophet 2000 or 2002. This supplements the original 256K, and the 256K added by the 877/878 kit, to bring the total to 1M. (The 877 or 878 must be installed prior to installing this kit.)

BANK SELECT

The instrument is now organized as two separate and complete memory banks. Only one bank is active at a time. To switch (toggle) from one memory bank to the other, hold PRESET while pressing EXECUTE. When you are in the second bank, the rightmost decimal point lights.

The bank can also be selected from MIDI. That is, MIDI program selects 0 - 11 address Bank 1, presets 1 - 12 (normal). MIDI program selects 12 - 23 address Bank 2, presets 1 - 12 (normal).

LOCAL ON/OFF

To switch (toggle) the local keyboard on and off from the front panel, select MIDI MODE and press EXECUTE. When the local keyboard is off, the leftmost decimal point lights.

BUGS FIXED

In MIDI Mode 4, program selections are now received (in the base channel).

In Mode 4, a MIDI Note Off used to turn off the same note number on all MIDI channels (not just the channel it is assigned to). This has been corrected.