

Eventide

the next step

Subject : H3000/3500 factory reinitialization procedure

According to Appendix F of H3000 UltraHarmonizer® manual:

- 1) Turn off H3000
- 2) Hold down "FUNCTION" key.
- 3) Keeping the key held down, power on H3000.
- 4) You will then see a message saying "Remove all presets ?". Release FUNCTION key.
- 5) You will usually want to enter NO !
- 6) Next you see "Reset the operating system".
- 7) Answer "Yes."
- 8) This will return enables, channel numbers etc to the way they were when the unit left the factory.
- 9) The H3000 will then restart itself.