



Editing Kits on the DTXPRESS III Kit

Once you have played the stock kits in the DTXPRESS III for a while you'll hear certain snare drums, kick drums, toms, etc. that you would like to combine into a personal kit. This "jump start" will walk you through the process of programming a kit combining your favorite voices.

The first time you build your own kit it's easiest to begin with a **FACTORY KIT** that you like and simply swap the snare drum. Since you can't make permanent changes to a factory kit, it will automatically be saved as a **USER KIT**. Once you have saved this kit we will replace other voices as well.

1. Select Kit #1 Acoustic Kit
2. Push the button that says **VOICE** and play the snare drum pad.
3. The screen will read **KIT IN=snare V=S/001**. The number 001 will be flashing.
4. Press the **VALUE +** button and play the pad. Each time you push the button you will advance to the next snare drum voice. When you find the snare drum you like press the **SAVE/ENT** button.
5. The screen will read **Store Drumkit =49 User Kit**. Press **SAVE/ENT** again. The screen will read Are You Sure?
6. Press **SAVE/ENT** again. The word **Complete!** Will flash on the screen, and it will read **KIT 49 Acoustic kit**.
7. Play the kit and you will hear the kit you saved with the new snare drum assigned.

To continue re-voicing this kit, repeat the procedure on the kick, toms, and cymbal pads. Each time you change the voice assigned to a pad, save the change before moving on to the next pad. This is a good habit to develop because if you change to a different kit before saving any changes, those changes will not be saved.

Once you have programmed a User Kit you will want to name it. Follow this procedure:

1. Press the **VOICE** button.
2. Press and hold the **PAGE DOWN** button. The screen will stop at **KIT Common Kit=Acoustic Kit**, the "A" will be flashing.
3. Press the **VALUE+** button until the first letter of the name you want to give the kit appears.
4. Press the **SEL>** button, the next letter will be flashing. Press the **VALUE+ or -** button until the next letter you want appears.

5. Repeat the process until the name you want to give the kit is complete. To delete any extra letters or symbols, press and hold the **VALUE-** button until a blank space appears. Press the **SEL>** button to select the next letter/symbol you want to delete, and repeat the process until all unwanted letters/symbols have been deleted.
6. Press the **SAVE/ENT** button. The new kit name will appear on the screen.